

SL5233 NEMO WIRELESS SWITCH/DIMMING CONTROLLER

Superlight Nemo is a contemporary design light switch that features dimming function and operates 100% wirelessly. The Nemo switch is battery powered and can be installed in any location. Nemo devices can be paired with any Superlight wireless receiver unit to control LED lighting products at a distance of up to 50mtrs. Superlight SL5233 Nemo controllers offer the appearance of a luxury switch/dimmer but are totally wireless. This makes Superlight Nemo ideal for projects where cable access is difficult or expensive.

SPECIFICATIONS

Nemo Switch Input Voltage:	CR2025 Coin Battery (included)
Rotary Knob Function	Click for On/Off + Press-Dimming
Dimming Control Range:	0.1-100%
Nemo Plate Dimensions:	77x77mm
Materials:	Glass Wall Plate + PVC Rocker Switch
Standard Colour/Finish:	Glass Facia
Output Control Channels:	1 Channel or 2 Channel
Connection Method:	RF Wireless
Compatible Receivers:	SL5411-00 / SL5439-32
RF Remote Operating Distance:	Up to 50mtrs +

PHOTOMETRIC INFORMATION

Detailed photometric reports are available by request
Superlight can provide wiring schematics and lighting control system design.
Contact us for more information.

Detailed photometric report and IES files available. Contact Superlight for more information. LM80, LM79 test reports available by request.

TYPICAL APPLICATIONS

Projects where traditional wiring is difficult or expensive
Domestic, commercial LED lighting installations.
Wireless control of superlight LED strips, modules and fittings.

CONTROL & DIMMING COMPATIBILITY

This product is available in dimmable configurations including Phase Dim, DALI, 1-10V, DMX512. Please contact us for options and availability.

INSTALLATION GUIDELINES

Nemo switches can be fixed to any surface using adhesive tape. They can be relocated at any time. Nemo can control multiple receivers simultaneously. Wireless receivers are available in constant-current or constant-voltage configurations.

ORDERING INFORMATION

SL5233-01	Nemo Glass Switch Wall Dimmer/Controller - Bat Operated RF 1 Gang
SL5233-02	Nemo Glass Switch Wall Dimmer/Controller - Bat Operated RF 2 Gang
SL5411-10	V3 RF Dimming Control Receiver - Constant Voltage 1x8A
SL5439-32	V3 RF Dimming Control Receiver - Constant Voltage 4x8A

CUSTOMISATION OPTIONS

Fixture colour can be refinished by special request
Superlight can design and supply dimming control or RGB control systems
Custom options may be subject to minimum order quantities

All product specifications are subject to change without notice. Superlight accepts no liabilities as a result of errors, updates or omissions. Please re-confirm all product details prior to ordering.

