

SL5411 SUPERLIGHT WIRELESS BUTTON DIMMER

Superlight wireless button dimmers are a revolutionary product that allows for wireless switching or dimming of Superlight LED products from virtually any location. The button dimmer pod can be fixed anywhere is powered by a small battery and they can be paired with a receiver unit at a distance of up to 50mtrs. Wireless buttons work instantly without cables so are ideal for projects where cable access is difficult or expensive.

SPECIFICATIONS

Wireless Button Input Voltage:	CR2025 Coin Battery (included)
Wireless Button Functions:	On/Off + Dimming
Dimming Control Range:	0.1-100%
Wireless Button Dimensions:	32mm (Round) 32x32mm (Square)
Wireless Button Thickness:	9.8mm
Output Control Channels:	1 Channel Per Button
Connection Method:	RF Wireless
RF Remote Operating Distance:	Up to 50mtrs +

PHOTOMETRIC INFORMATION

Detailed photometric reports are available by request
Superlight can provide wiring schematics and lighting control system design.
Contact us for more information.

Detailed photometric report and IES files available. Contact Superlight for more information. LM80, LM79 test reports available by request.

TYPICAL APPLICATIONS

Projects where traditional wiring is difficult or expensive,
Domestic, commercial LED lighting installations.
Wireless control of superlight LED strips, modules and fittings.

CONTROL & DIMMING COMPATIBILITY

This product is available in dimmable configurations including Phase Dim, DALI, 1-10V, DMX512. Please contact us for options and availability.

INSTALLATION GUIDELINES

Wireless Button can be fixed to any surface using adhesive tape.
Wireless Button can control multiple receivers simultaneously
Wireless receivers available in constant-current or constant-voltage configurations.

ORDERING INFORMATION

SL5411-20	Wireless Button Dimmer - Bat Powered RF Wireless On/Off+Dim Round
SL5411-40	Wireless Button Dimmer - Bat Powered RF Wireless On/Off+Dim Square
SL5411-10	V3 RF Dimming Control Receiver - Constant Voltage Single Channel
SL5439-32	V3 RF Dimming Control Receiver - Constant Voltage RGB/RGBW

CUSTOMISATION OPTIONS

Fixture colour can be refinished by special request
Superlight can design and supply dimming control or RGB control systems
Custom options may be subject to minimum order quantities

All product specifications are subject to change without notice. Superlight accepts no liabilities as a result of errors, updates or omissions. Please re-confirm all product details prior to ordering.

